

Información técnica de los Pararrayos YH10W.

Escribe	Voltaje nominal	MCOV(KV)	Uso máximo de voltaje residual un impulso de corriente 8/20 (kV)			fuga Distancia (mm)	Arco seco Distancia (mm)
			5.0kA	10kA	20kA		
YH10W-3	3	2.55	7.5	8.2	9.2	250	146
YH10W-6	6	5.1	15.1	16.3	18.4	250	146
YH10W-9	9	7.65	22.6	24.5	27.5	370	178
YH10W-12	12	10.2	30.1	32.6	36.5	520	214
YH10W-15	15	12.7	37.7	40.8	46.1	650	250
YH10W-18	18	15.3	45.2	48.9	55.3	650	250
YH10W-21	21	17	52.7	57.1	64.3	790	284
YH10W-24	24	19.5	60.3	65.2	73.5	920	318
YH10W-27	27	22	67.8	73.4	82.6	1050	356
YH10W-30	30	24.4	75.4	81.6	91.6	1200	392
YH10W-33	33	26.7	82.9	89.7	99.5	1340	428
YH10W-36	36	29	90.4	97.9	109.6	1340	428